Freescale Semiconductor
Technical Data

Document Number: MRF1518
Rev. 7, 5/2006


Replaced by MRF1518NT1. There are no form, fit or function changes with this part replacement. N suffix added to part number to indicate transition to lead-free terminations.

RF Power Field Effect Transistor

N-Channel Enhancement-Mode Lateral MOSFET


Designed for broadband commercial and industrial applications with frequencies to 520 MHz. The high gain and broadband performance of this device make it ideal for large-signal, common source amplifier applications in 12.5 volt mobile FM equipment.

- Specified Performance @ 520 MHz, 12.5 Volts
  Output Power — 8 Watts
  Power Gain — 11 dB
  Efficiency — 55%
- Capable of Handling 20:1 VSWR, @ 15.5 Vdc, 520 MHz, 2 dB Overdrive
- Excellent Thermal Stability
- Characterized with Series Equivalent Large-Signal Impedance Parameters
- Broadband UHF/VHF Demonstration Amplifier Information Available Upon Request
- Available in Tape and Reel. T1 Suffix = 1,000 Units per 12 mm, 7 Inch Reel.



MRF1518T1

**520 MHz, 8 W, 12.5 V
LATERAL N-CHANNEL
BROADBAND
RF POWER MOSFET**



**CASE 466-03, STYLE 1
PLD-1.5**

PLASTIC

ARCHIVE INFORMATION

ARCHIVE INFORMATION

Table 1. Maximum Ratings

Rating	Symbol	Value	Unit
Drain-Source Voltage	V_{DSS}	-0.5, +40	Vdc
Gate-Source Voltage	V_{GS}	±20	Vdc
Drain Current — Continuous	I_D	4	Adc
Total Device Dissipation @ T_C = 25°C (1) Derate above 25°C	P_D	62.5 0.50	W W/°C
Storage Temperature Range	T_{stg}	-65 to +150	°C
Operating Junction Temperature	T_J	150	°C

Table 2. Thermal Characteristics

Characteristic	Symbol	Value	Unit
Thermal Resistance, Junction to Case	$R_{\theta JC}$	2	°C/W

Table 3. Moisture Sensitivity Level

Test Methodology	Rating	Package Peak Temperature	Unit
Per JESD 22-A113, IPC/JEDEC J-STD-020	1	260	°C

1. Calculated based on the formula $P_D = \frac{T_J - T_C}{R_{\theta JC}}$

NOTE - **CAUTION** - MOS devices are susceptible to damage from electrostatic charge. Reasonable precautions in handling and packaging MOS devices should be observed.

© Freescale Semiconductor, Inc., 2006. All rights reserved.


freescale™ semiconductor

Table 4. Electrical Characteristics (T_C = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
Off Characteristics					
Zero Gate Voltage Drain Current (V_{DS} = 40 Vdc, V_{GS} = 0 Vdc)	I_{DSS}	—	—	1	μAdc
Gate-Source Leakage Current (V_{GS} = 10 Vdc, V_{DS} = 0 Vdc)	I_{GSS}	—	—	1	μAdc
On Characteristics					
Gate Threshold Voltage (V_{DS} = 12.5 Vdc, I_D = 100 μA)	$V_{GS(th)}$	1.0	1.6	2.1	Vdc
Drain-Source On-Voltage (V_{GS} = 10 Vdc, I_D = 1 Adc)	$V_{DS(on)}$	—	0.4	—	Vdc
Dynamic Characteristics					
Input Capacitance (V_{DS} = 12.5 Vdc, V_{GS} = 0, f = 1 MHz)	C_{iss}	—	66	—	pF
Output Capacitance (V_{DS} = 12.5 Vdc, V_{GS} = 0, f = 1 MHz)	C_{oss}	—	33	—	pF
Reverse Transfer Capacitance (V_{DS} = 12.5 Vdc, V_{GS} = 0, f = 1 MHz)	C_{rss}	—	4.5	—	pF
Functional Tests (In Freescale Test Fixture)					
Common-Source Amplifier Power Gain (V_{DD} = 12.5 Vdc, P_{out} = 8 Watts, I_{DQ} = 150 mA, f = 520 MHz)	G_{ps}	10	11	—	dB
Drain Efficiency (V_{DD} = 12.5 Vdc, P_{out} = 8 Watts, I_{DQ} = 150 mA, f = 520 MHz)	η	50	55	—	%

ARCHIVE INFORMATION
ARCHIVE INFORMATION

ARCHIVE INFORMATION



B1, B2	Short Ferrite Beads, Fair Rite Products (2743021446)	R4	33 kΩ, 1/8 W Resistor
C1, C12	240 pF, 100 mil Chip Capacitors	Z1	0.451″ x 0.080″ Microstrip
C2, C3, C10, C11	0 to 20 pF Trimmer Capacitors	Z2	1.005″ x 0.080″ Microstrip
C4	82 pF, 100 mil Chip Capacitor	Z3	0.020″ x 0.080″ Microstrip
C5, C16	120 pF, 100 mil Chip Capacitors	Z4	0.155″ x 0.080″ Microstrip
C6, C13	10 μF, 50 V Electrolytic Capacitors	Z5, Z6	0.260″ x 0.223″ Microstrip
C7, C14	1,200 pF, 100 mil Chip Capacitors	Z7	0.065″ x 0.080″ Microstrip
C8, C15	0.1 μF, 100 mil Chip Capacitors	Z8	0.266″ x 0.080″ Microstrip
C9	30 pF, 100 mil Chip Capacitor	Z9	1.113″ x 0.080″ Microstrip
L1	55.5 nH, 5 Turn, Coilcraft	Z10	0.433″ x 0.080″ Microstrip
N1, N2	Type N Flange Mounts	Board	Glass Teflon®, 31 mils, 2 oz. Copper
R1	15 Ω Chip Resistor (0805)		
R2	51 Ω, 1/2 W Resistor		
R3	10 Ω Chip Resistor (0805)		

Figure 1. 450 - 520 MHz Broadband Test Circuit

TYPICAL CHARACTERISTICS, 450 - 520 MHz




Figure 2. Output Power versus Input Power




Figure 3. Input Return Loss versus Output Power

ARCHIVE INFORMATION

ARCHIVE INFORMATION

TYPICAL CHARACTERISTICS, 450 - 520 MHz




Figure 4. Gain versus Output Power




Figure 5. Drain Efficiency versus Output Power




Figure 6. Output Power versus Biasing Current




Figure 7. Drain Efficiency versus Biasing Current




Figure 8. Output Power versus Supply Voltage





Figure 9. Drain Efficiency versus Supply Voltage

ARCHIVE INFORMATION



B1, B2	Long Ferrite Beads, Fair Rite Products	N1, N2	Type N Flange Mounts
C1, C9	12 pF, 100 mil Chip Capacitors	R1	47 Ω Chip Resistor (0805)
C2	6.8 pF, 100 mil Chip Capacitor	Z1	1.145″ x 0.080″ Microstrip
C3, C4	20 pF, 100 mil Chip Capacitors	Z2	0.786″ x 0.080″ Microstrip
C5	51 pF, 100 mil Chip Capacitor	Z3	0.115″ x 0.223″ Microstrip
C6, C13	1000 pF, 100 mil Chip Capacitors	Z4	0.145″ x 0.223″ Microstrip
C7, C14	0.039 μF, 100 mil Chip Capacitors	Z5	0.260″ x 0.223″ Microstrip
C8	1 μF, 20 V Tantalum Chip Capacitor	Z6	0.081″ x 0.080″ Microstrip
C10	3 pF, 100 mil Chip Capacitor	Z7	0.104″ x 0.080″ Microstrip
C11, C12	51 pF, 100 mil Chip Capacitors	Z8	1.759″ x 0.080″ Microstrip
C15	22 μF, 35 V Tantalum Chip Capacitor	Board	Glass Teflon®, 31 mils, 2 oz. Copper
L1, L2	18.5 nH, 5 Turn, Coilcraft		

Figure 10. 820 - 850 MHz Broadband Test Circuit

TYPICAL CHARACTERISTICS, 820 - 850 MHz




Figure 11. Output Power versus Input Power




Figure 12. Input Return Loss versus Output Power

ARCHIVE INFORMATION
ARCHIVE INFORMATION

ARCHIVE INFORMATION

TYPICAL CHARACTERISTICS, 820 - 850 MHz




Figure 13. Gain versus Output Power




Figure 14. Drain Efficiency versus Output Power




Figure 15. Output Power versus Biasing Current




Figure 16. Drain Efficiency versus Biasing Current




Figure 17. Output Power versus Supply Voltage





Figure 18. Drain Efficiency versus Supply Voltage

ARCHIVE INFORMATION

ARCHIVE INFORMATION



B1, B2	Short Ferrite Beads, Fair Rite Products (2743021446)	R3	10 Ω Chip Resistor (0805)
C1, C14	240 pF, 100 mil Chip Capacitors	R4	33 kΩ, 1/8 W Resistor
C2, C3, C4, C11, C12, C13	0 to 20 pF Trimmer Capacitors	Z1	0.476″ x 0.080″ Microstrip
C5	30 pF, 100 mil Chip Capacitor	Z2	0.724″ x 0.080″ Microstrip
C6	47 pF, 100 mil Chip Capacitor	Z3	0.348″ x 0.080″ Microstrip
C7, C18	120 pF, 100 mil Chip Capacitors	Z4	0.048″ x 0.080″ Microstrip
C8, C15	10 μF, 50 V Electrolytic Capacitors	Z5	0.175″ x 0.080″ Microstrip
C9, C16	1,200 pF, 100 mil Chip Capacitors	Z6, Z7	0.260″ x 0.223″ Microstrip
C10, C17	0.1 μF, 100 mil Chip Capacitors	Z8	0.239″ x 0.080″ Microstrip
L1	55.5 nH, 5 Turn, Coilcraft	Z9	0.286″ x 0.080″ Microstrip
N1, N2	Type N Flange Mounts	Z10	0.806″ x 0.080″ Microstrip
R1	15 Ω Chip Resistor (0805)	Z11	0.553″ x 0.080″ Microstrip
R2	51 Ω, 1/2 W Resistor	Board	Glass Teflon®, 31 mils, 2 oz. Copper

Figure 19. 400 - 470 MHz Broadband Test Circuit

TYPICAL CHARACTERISTICS, 400 - 470 MHz




Figure 20. Output Power versus Input Power




Figure 21. Input Return Loss versus Output Power

ARCHIVE INFORMATION

ARCHIVE INFORMATION

ARCHIVE INFORMATION

TYPICAL CHARACTERISTICS, 400 - 470 MHz




Figure 22. Gain versus Output Power




Figure 23. Drain Efficiency versus Output Power




Figure 24. Output Power versus Biasing Current




Figure 25. Drain Efficiency versus Biasing Current




Figure 26. Output Power versus Supply Voltage





Figure 27. Drain Efficiency versus Supply Voltage

ARCHIVE INFORMATION



B1, B2	Short Ferrite Beads, Fair Rite Products (2743021446)	L4	55.5 nH, 5 Turn, Coilcraft
C1, C13	330 pF, 100 mil Chip Capacitors	N1, N2	Type N Flange Mounts
C2, C4, C11	0 to 20 pF Trimmer Capacitors	R1	15 Ω Chip Resistor (0805)
C3	12 pF, 100 mil Chip Capacitor	R2	56 Ω, 1/4 W Carbon Resistor
C5	43 pF, 100 mil Chip Capacitor	R3	100 Ω Chip Resistor (0805)
C6, C17	75 pF, 100 mil Chip Capacitors	R4	33 kΩ, 1/8 W Carbon Resistor
C7, C14	10 μF, 50 V Electrolytic Capacitors	Z1	0.115″ x 0.080″ Microstrip
C8, C15	1,200 pF, 100 mil Chip Capacitors	Z2	0.255″ x 0.080″ Microstrip
C9, C16	0.1 μF, 100 mil Chip Capacitors	Z3	1.037″ x 0.080″ Microstrip
C10	75 pF, 100 mil Chip Capacitor	Z4	0.192″ x 0.080″ Microstrip
C12	13 pF, 100 mil Chip Capacitor	Z5, Z6	0.260″ x 0.223″ Microstrip
L1	26 nH, 4 Turn, Coilcraft	Z7	0.125″ x 0.080″ Microstrip
L2	5 nH, 2 Turn, Coilcraft	Z8	0.962″ x 0.080″ Microstrip
L3	33 nH, 5 Turn, Coilcraft	Z9	0.305″ x 0.080″ Microstrip
		Z10	0.155″ x 0.080″ Microstrip
		Board	Glass Teflon®, 31 mils, 2 oz. Copper

Figure 28. 135 - 175 MHz Broadband Test Circuit

TYPICAL CHARACTERISTICS, 135 - 175 MHz




Figure 29. Output Power versus Input Power




Figure 30. Input Return Loss versus Output Power

ARCHIVE INFORMATION

ARCHIVE INFORMATION

ARCHIVE INFORMATION

TYPICAL CHARACTERISTICS, 135 - 175 MHz




Figure 31. Gain versus Output Power




Figure 32. Drain Efficiency versus Output Power




Figure 33. Output Power versus Biasing Current




Figure 34. Drain Efficiency versus Biasing Current




Figure 35. Output Power versus Supply Voltage






Figure 36. Drain Efficiency versus Supply Voltage

ARCHIVE INFORMATION





V_{DD} = 12.5 V, I_{DQ} = 150 mA, P_{out} = 8 W

f MHz	Z_{in} Ω	Z_{OL}* Ω
450	4.9 +j2.85	6.42 +j3.23
470	4.85 +j3.71	4.59 +j3.61
500	4.63 +j3.84	4.72 +j3.12
520	3.52 +j3.92	3.81 +j3.27

Z_{in} = Complex conjugate of source impedance with parallel 15 Ω resistor and 82 pF capacitor in series with gate. (See Figure 1).

Z_{OL}* = Complex conjugate of the load impedance at given output power, voltage, frequency, and η_D > 50 %.

V_{DD} = 12.5 V, I_{DQ} = 150 mA, P_{out} = 8 W

f MHz	Z_{in} Ω	Z_{OL}* Ω
820	1.42 -j0.32	2.34 +j0.23
830	1.39 -j0.21	2.36 +j0.47
840	1.32 -j0.16	2.40 +j0.69
850	1.23 -j0.13	2.37 +j0.79

Z_{in} = Complex conjugate of source impedance.

Z_{OL}* = Complex conjugate of the load impedance at given output power, voltage, frequency, and η_D > 50 %.

Note: Z_{OL}* was chosen based on tradeoffs between gain, drain efficiency, and device stability.





Figure 37. Series Equivalent Input and Output Impedance

ARCHIVE INFORMATION

ARCHIVE INFORMATION

ARCHIVE INFORMATION



V_{DD} = 12.5 V, I_{DQ} = 150 mA, P_{out} = 8 W

f MHz	Z_{in} Ω	Z_{OL}* Ω
400	4.28 +j2.36	4.41 +j0.67
440	6.45 +j5.13	4.14 +j2.53
470	5.91 +j3.34	3.92 +j4.02

V_{DD} = 12.5 V, I_{DQ} = 150 mA, P_{out} = 8 W

f MHz	Z_{in} Ω	Z_{OL}* Ω
135	18.31 -j0.76	8.97 +j2.62
155	17.72 +j1.85	9.69 +j2.81
175	18.06 +j5.23	7.94 +j1.14

Z_{in} = Complex conjugate of source impedance with parallel 15 Ω resistor and 47 pF capacitor in series with gate. (See Figure 19).

Z_{OL}* = Complex conjugate of the load impedance at given output power, voltage, frequency, and η_D > 50 %.

Z_{in} = Complex conjugate of source impedance with parallel 15 Ω resistor and 43 pF capacitor in series with gate. (See Figure 28).

Z_{OL}* = Complex conjugate of the load impedance at given output power, voltage, frequency, and η_D > 50 %.

Note: Z_{OL}* was chosen based on tradeoffs between gain, drain efficiency, and device stability.




Figure 37. Series Equivalent Input and Output Impedance (continued)

Table 5. Common Source Scattering Parameters (V_{DD} = 12.5 Vdc)

I_{DQ} = 150 mA

f	S_{11}		S_{21}		S_{12}		S_{22}	
MHz	$\|S_{11}\|$	∠ϕ	$\|S_{21}\|$	∠ϕ	$\|S_{12}\|$	∠ϕ	$\|S_{22}\|$	∠ϕ
50	0.88	-148	18.91	99	0.033	11	0.67	-144
100	0.85	-163	9.40	86	0.033	-6	0.66	-158
200	0.85	-170	4.47	73	0.026	-17	0.69	-162
300	0.87	-171	2.72	64	0.025	-28	0.74	-163
400	0.88	-172	1.85	56	0.021	-21	0.79	-164
500	0.90	-173	1.35	52	0.019	-30	0.83	-165
600	0.92	-173	1.04	47	0.014	-26	0.85	-167
700	0.93	-174	0.83	44	0.015	-39	0.88	-168
800	0.94	-175	0.68	39	0.014	-31	0.90	-169
900	0.94	-175	0.55	36	0.010	-41	0.91	-170
1000	0.96	-176	0.46	30	0.011	-38	0.95	-170

I_{DQ} = 800 mA

f	S_{11}		S_{21}		S_{12}		S_{22}	
MHz	$\|S_{11}\|$	∠ϕ	$\|S_{21}\|$	∠ϕ	$\|S_{12}\|$	∠ϕ	$\|S_{22}\|$	∠ϕ
50	0.90	-159	20.80	97	0.020	14	0.73	-162
100	0.88	-169	10.35	88	0.018	1	0.74	-169
200	0.88	-174	5.09	79	0.017	-9	0.75	-171
300	0.89	-175	3.23	73	0.015	-18	0.77	-171
400	0.89	-175	2.30	67	0.015	-17	0.80	-171
500	0.90	-176	1.74	63	0.014	-22	0.82	-170
600	0.91	-176	1.39	59	0.014	-19	0.83	-171
700	0.92	-176	1.16	55	0.009	-23	0.85	-171
800	0.93	-176	0.96	50	0.011	-14	0.87	-172
900	0.94	-177	0.80	46	0.007	4	0.88	-173
1000	0.94	-177	0.67	41	0.010	-15	0.89	-173

I_{DQ} = 1.5 A

f	S_{11}		S_{21}		S_{12}		S_{22}	
MHz	$\|S_{11}\|$	∠ϕ	$\|S_{21}\|$	∠ϕ	$\|S_{12}\|$	∠ϕ	$\|S_{22}\|$	∠ϕ
50	0.91	-159	20.18	97	0.015	11	0.73	-165
100	0.89	-169	10.05	89	0.016	-5	0.74	-171
200	0.88	-174	4.93	80	0.015	-3	0.75	-172
300	0.89	-175	3.14	73	0.014	-14	0.78	-172
400	0.89	-176	2.24	67	0.014	-20	0.80	-171
500	0.90	-176	1.70	64	0.014	-22	0.82	-170
600	0.92	-176	1.36	59	0.010	-16	0.84	-171
700	0.92	-176	1.13	55	0.013	-10	0.85	-171
800	0.93	-177	0.94	50	0.008	-13	0.87	-172
900	0.94	-177	0.78	46	0.013	-26	0.87	-173
1000	0.94	-178	0.65	41	0.007	8	0.87	-172

ARCHIVE INFORMATION
ARCHIVE INFORMATION

ARCHIVE INFORMATION

ARCHIVE INFORMATION

APPLICATIONS INFORMATION

DESIGN CONSIDERATIONS

This device is a common-source, RF power, N-Channel enhancement mode, Lateral Metal-Oxide Semiconductor Field-Effect Transistor (MOSFET). Freescale Application Note AN211A, "FETs in Theory and Practice", is suggested reading for those not familiar with the construction and characteristics of FETs.

This surface mount packaged device was designed primarily for VHF and UHF portable power amplifier applications. Manufacturability is improved by utilizing the tape and reel capability for fully automated pick and placement of parts. However, care should be taken in the design process to insure proper heat sinking of the device.


The major advantages of Lateral RF power MOSFETs include high gain, simple bias systems, relative immunity from thermal runaway, and the ability to withstand severely mismatched loads without suffering damage.

MOSFET CAPACITANCES

The physical structure of a MOSFET results in capacitors between all three terminals. The metal oxide gate structure determines the capacitors from gate-to-drain (C_{gd}), and gate-to-source (C_{gs}). The PN junction formed during fabrication of the RF MOSFET results in a junction capacitance from drain-to-source (C_{ds}). These capacitances are characterized as input (C_{iss}), output (C_{oss}) and reverse transfer (C_{rss}) capacitances on data sheets. The relationships between the inter-terminal capacitances and those given on data sheets are shown below. The C_{iss} can be specified in two ways:

1. Drain shorted to source and positive voltage at the gate.
2. Positive voltage of the drain in respect to source and zero volts at the gate.

In the latter case, the numbers are lower. However, neither method represents the actual operating conditions in RF applications.



DRAIN CHARACTERISTICS

One critical figure of merit for a FET is its static resistance in the full-on condition. This on-resistance, $R_{DS(on)}$, occurs in the linear region of the output characteristic and is specified at a specific gate-source voltage and drain current. The drain-source voltage under these conditions is termed $V_{DS(on)}$. For MOSFETs, $V_{DS(on)}$ has a positive temperature coefficient at high temperatures because it contributes to the power dissipation within the device.

BV_{DSS} values for this device are higher than normally required for typical applications. Measurement of BV_{DSS} is not recommended and may result in possible damage to the device.

GATE CHARACTERISTICS

The gate of the RF MOSFET is a polysilicon material, and is electrically isolated from the source by a layer of oxide. The DC input resistance is very high - on the order of $10^9\ \Omega$ — resulting in a leakage current of a few nanoamperes.

Gate control is achieved by applying a positive voltage to the gate greater than the gate-to-source threshold voltage, $V_{GS(th)}$.

Gate Voltage Rating — Never exceed the gate voltage rating. Exceeding the rated V_{GS} can result in permanent damage to the oxide layer in the gate region.

Gate Termination — The gates of these devices are essentially capacitors. Circuits that leave the gate open-circuited or floating should be avoided. These conditions can result in turn-on of the devices due to voltage build-up on the input capacitor due to leakage currents or pickup.

Gate Protection — These devices do not have an internal monolithic zener diode from gate-to-source. If gate protection is required, an external zener diode is recommended. Using a resistor to keep the gate-to-source impedance low also helps dampen transients and serves another important function. Voltage transients on the drain can be coupled to the gate through the parasitic gate-drain capacitance. If the gate-to-source impedance and the rate of voltage change on the drain are both high, then the signal coupled to the gate may be large enough to exceed the gate-threshold voltage and turn the device on.

DC BIAS

Since this device is an enhancement mode FET, drain current flows only when the gate is at a higher potential than the source. RF power FETs operate optimally with a quiescent drain current (I_{DQ}), whose value is application dependent. This device was characterized at I_{DQ} = 150 mA, which is the suggested value of bias current for typical applications. For special applications such as linear amplification, I_{DQ} may have to be selected to optimize the critical parameters.

The gate is a dc open circuit and draws no current. Therefore, the gate bias circuit may generally be just a simple resistive divider network. Some special applications may require a more elaborate bias system.

GAIN CONTROL

Power output of this device may be controlled to some degree with a low power dc control signal applied to the gate, thus facilitating applications such as manual gain control, ALC/AGC and modulation systems. This characteristic is very dependent on frequency and load line.

ARCHIVE INFORMATION

ARCHIVE INFORMATION

MOUNTING

The specified maximum thermal resistance of 2°C/W assumes a majority of the 0.065″ x 0.180″ source contact on the back side of the package is in good contact with an appropriate heat sink. As with all RF power devices, the goal of the thermal design should be to minimize the temperature at the back side of the package. Refer to Freescale Application Note AN4005/D, “Thermal Management and Mounting Method for the PLD-1.5 RF Power Surface Mount Package,” and Engineering Bulletin EB209/D, “Mounting Method for RF Power Leadless Surface Mount Transistor” for additional information.

AMPLIFIER DESIGN

Impedance matching networks similar to those used with bipolar transistors are suitable for this device. For examples see Freescale Application Note AN721, “Impedance Matching Networks Applied to RF Power Transistors.” Large-signal impedances are provided, and will yield a good first pass approximation.

Since RF power MOSFETs are triode devices, they are not unilateral. This coupled with the very high gain of this device yields a device capable of self oscillation. Stability may be achieved by techniques such as drain loading, input shunt resistive loading, or output to input feedback. The RF test fixture implements a parallel resistor and capacitor in series with the gate, and has a load line selected for a higher efficiency, lower gain, and more stable operating region.


Two-port stability analysis with this device’s S-parameters provides a useful tool for selection of loading or feedback circuitry to assure stable operation. See Freescale Application Note AN215A, “RF Small-Signal Design Using Two-Port Parameters” for a discussion of two port network theory and stability.


NOTES

NOTES


NOTES

PACKAGE DIMENSIONS






VIEW Y-Y



NOTES:
1. INTERPRET DIMENSIONS AND TOLERANCES PER ASME Y14.5M, 1984.
2. CONTROLLING DIMENSION: INCH
3. RESIN BLEED/FLASH ALLOWABLE IN ZONE V, W, AND X.

STYLE 1:
PIN 1. DRAIN
2. GATE
3. SOURCE
4. SOURCE

CASE 466-03
ISSUE D
PLD-1.5
PLASTIC



(inches / mm)

SOLDER FOOTPRINT

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.255	0.265	6.48	6.73
B	0.225	0.235	5.72	5.97
C	0.065	0.072	1.65	1.83
D	0.130	0.150	3.30	3.81
E	0.021	0.026	0.53	0.66
F	0.026	0.044	0.66	1.12
G	0.050	0.070	1.27	1.78
H	0.045	0.063	1.14	1.60
J	0.160	0.180	4.06	4.57
K	0.273	0.285	6.93	7.24
L	0.245	0.255	6.22	6.48
N	0.230	0.240	5.84	6.10
P	0.000	0.008	0.00	0.20
Q	0.055	0.063	1.40	1.60
R	0.200	0.210	5.08	5.33
S	0.006	0.012	0.15	0.31
U	0.006	0.012	0.15	0.31
ZONE V	0.000	0.021	0.00	0.53
ZONE W	0.000	0.010	0.00	0.25
ZONE X	0.000	0.010	0.00	0.25

How to Reach Us:

Home Page:
www.freescale.com

E-mail:
support@freescale.com

USA/Europe or Locations Not Listed:
Freescale Semiconductor
Technical Information Center, CH370
1300 N. Alma School Road
Chandler, Arizona 85224
+1-800-521-6274 or +1-480-768-2130
support@freescale.com

Europe, Middle East, and Africa:
Freescale Halbleiter Deutschland GmbH
Technical Information Center
Schatzbogen 7
81829 Muenchen, Germany
+44 1296 380 456 (English)
+46 8 52200080 (English)
+49 89 92103 559 (German)
+33 1 69 35 48 48 (French)
support@freescale.com

Japan:
Freescale Semiconductor Japan Ltd.
Headquarters
ARCO Tower 15F
1-8-1, Shimo-Meguro, Meguro-ku,
Tokyo 153-0064
Japan
0120 191014 or +81 3 5437 9125
support.japan@freescale.com

Asia/Pacific:
Freescale Semiconductor Hong Kong Ltd.
Technical Information Center
2 Dai King Street
Tai Po Industrial Estate
Tai Po, N.T., Hong Kong
+800 2666 8080
support.asia@freescale.com

For Literature Requests Only:
Freescale Semiconductor Literature Distribution Center
P.O. Box 5405
Denver, Colorado 80217
1-800-441-2447 or 303-675-2140
Fax: 303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

RoHS-compliant and/or Pb- free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb- free counterparts. For further information, see http://www.freescale.com or contact your Freescale sales representative.

For information on Freescale.s Environmental Products program, go to http://www.freescale.com/epp.

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. “Typical” parameters that may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including “Typicals”, must be validated for each customer application by customer’s technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.

Freescale™ and the Freescale logo are trademarks of Freescale Semiconductor, Inc. All other product or service names are the property of their respective owners.
© Freescale Semiconductor, Inc. 2006. All rights reserved.

RoHS-compliant and/or Pb-free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb-free counterparts. For further information, see http://www.freescale.com or contact your Freescale sales representative.

For information on Freescale’s Environmental Products program, go to http://www.freescale.com/epp.

freescale™ semiconductor

Document Number: MRF1518
Rev. 7, 5/2006